

# FA05

## Three-Phase Passive Filters



**FA05** series is specially designed for the knock down of current harmonics generated by U.P.S, in industrial applications. The passive filter is realized by tuning in frequency a capacitor bank and a three-phase reactance. In this way there is a resonant circuit which is chosen as the preferential way from the harmonic current which is to be reduced: in fact, the filter has a sufficiently low impedance value only at the frequency value to which it is tuned.

### PERFORMANCE DATA

- **Rated voltage** 400 Vac (others on request)
- **Rated frequency** 50 Hz (60 Hz on request)
- **Insulation voltage** 690 Vac
- **auxiliary voltage** 230 Vac (110 Vac on request)
- **Overvoltage** 1,1 Un (rated voltage)
- **Temperature range** -5 / +40 °C
- **Impulse withstand** 8 kV

### TUNED FILTER

5° grade Harmonic

### TECHNICAL DATA

|                                     |   |
|-------------------------------------|---|
| <b>Enclosures</b>                   | Made of sheet steel, protected against corrosion by phosphating and epoxy powder coating. RAL 7032 colour (others on request). Degree of protection: external panel IP 31 (others on request); internal panel IP 20 at the input of power cables (IP 20 with open doors on request).  |
| <b>Ventilation</b>                  | Forced.   |
| <b>Thermal protection</b>           | Made by means of two thermoprobes. The first, with an operating threshold of 35 ° C, controls the insertion of the cooling fans on the roof. The second (50 ° C) separates the filter branch if the temperature exceeds the maximum allowed limit. When the phenomenon ceases, there is automatic recovery.   |
| <b>Insertion</b>                    | Manual, or automatic piloted remotely (commands by the installer).  |
| <b>Supply</b>                       | To be carried out directly on the line choke or on the power supply of the fuses.<br>Three-phase input + grounding cable from below for G6E and G8E cabinets. The termination of an NC contact of max 5 Amps 250 Vac for the remote indication of the operation of the equipment is provided by a terminal board. If not used, the remote control must be short-circuited.  |
| <b>Signals</b>                      | On the front of each panel there is a luminous signal with green light for a live panel, the selector for the insertion of the filter with white light, the intervention of the amperometric protection with yellow light and the relative reset button, the intervention maximum temperature with yellow light signal..  |
| <b>3-pole contactors</b>            | Each battery is switched on / off by a three-pole contactor (Class AC6-b) to offer high reliability.  |
| <b>Fuses</b>                        | Each capacitors bank is protected by fuses. The protection system of both the power circuits (NH-00 curve gG fuses) and the auxiliary ones (isolable fuse holders and 10.3x38 fuses) foresees the use of high breaking power fuses (100kA).   |
| <b>Capacitors</b>                   | Single-phase capacitors in self-healing metallized polypropylene (MKP), equipped with an anti-burst device and discharge resistance. They are impregnated in vegetable oil, PCB free. Delta connection. Type of continuous service. <ul style="list-style-type: none"><li>• <b>rated voltage: 500 Vac</b></li><li>• overvoltage: 1.1 x A (8h / 24h)</li><li>• current overload: 1.3 x In</li><li>• capacity tolerance: -5% / + 10%</li><li>• losses due to dissipation: ≤0.4 W / kvar</li><li>• temperature category: -25 / D</li></ul> |
| <b>Line reactor</b><br>(on request) | It is manufactured using magnetic low losses core plates. When used, it allows the decoupling of the load and the filter from the network for a correct current sharing between the network and the filter. It also ensures the correct operation of the filter in case of varying distortion in the network.   |

**Filtering reactor** It is manufactured using magnetic low losses core plates and it is tuned with the capacitors. Class H and linearity up to 2In.

- agreement frequency of 245Hz (FA05)
- losses due to dissipation: depending on the power of the filter
- maximum possible harmonic distortion in the THD network ( $v$ ) = 5% (others on request).

**Amperometric protection** Protects condenser banks by disabling them in case of overcurrents.

## QUALITY AND TESTING

**Regulations** Capacitors: IEC/EN 60831-1 / 2 certified by IMQ (V1927); Equipment: IEC/EN 61439-1 / 2, IEC/EN 61921.

**European directives** Low voltage: 2014/35/CE; Electromagnetic compatibility: 2014/30/CE.

**Testing** 100% of the automatic equipment is subject to visual inspection, insulation test: phase-phase and phase-earth, battery efficiency and ventilation circuit control: the report is included in the documentation. The capacitors are tested in three consecutive stages of the production process: after winding, regeneration and before labeling.

## CONFIGURATION

### General notes

- The rated power is expressed at 400 V - 50 Hz.
- The choice of supply cables depends on the installation conditions, the length of the same and the ambient temperature. For a correct sizing, refer to the IEC 60364-5, CEI 64-8 and the UNEL 35024/01 standards.

The application of the filters involves an in-depth analysis of the operating conditions of the system.

Below is a list of the information essential for a correct sizing:

- Nominal data and operating cycle of the load to be filtered.
- Campaign of harmonic distortion measurements, to determine the frequency and the value of the harmonic current to be reduced.
- Electrical scheme of the system, with indication of the installation point of the filter.
- Presence of power factor correction equipment (automatic or fixed), type and location.
- Nominal data of other distorting loads present in the system.

### Table

| Code         | Load Data              |                 |               | Filter Data                         |                |                  |                          |          |        |
|--------------|------------------------|-----------------|---------------|-------------------------------------|----------------|------------------|--------------------------|----------|--------|
|              | Max. power load U.P.S. | Pn <sup>1</sup> | Rated current | 5th harmonic current to be filtered | Reactive power | Reactive current | Impact resistance degree | Type     | Weight |
|              | (kVA)                  | (kW)            | (A)           | (A)                                 | (kvar)         | (A)              |                          | (mm)     | (kg)   |
| FA05 15-400  | 15                     | 12              | 22            | 8                                   | 6              | 9                | IK05                     | G6E      | 60     |
| FA05 20-400  | 20                     | 16              | 30            | 12                                  | 8              | 11               | IK05                     | G6E      | 71     |
| FA05 30-400  | 30                     | 24              | 42            | 16                                  | 10             | 14               | IK05                     | G6E      | 79     |
| FA05 40-400  | 40                     | 32              | 60            | 24                                  | 13             | 19               | IK05                     | G6E      | 95     |
| FA05 55-400  | 55                     | 44              | 80            | 32                                  | 18             | 25               | IK05                     | G6E      | 105    |
| FA05 70-400  | 70                     | 56              | 100           | 40                                  | 22             | 32               | IK05                     | G6E      | 115    |
| FA05 90-400  | 90                     | 72              | 130           | 52                                  | 26             | 38               | IK10                     | G6E      | 240    |
| FA05 110-400 | 110                    | 88              | 160           | 64                                  | 32             | 46               | IK10                     | G8E      | 265    |
| FA05 140-400 | 140                    | 112             | 200           | 80                                  | 41             | 59               | IK10                     | G8E      | 280    |
| FA05 180-400 | 180                    | 144             | 260           | 105                                 | 52             | 75               | IK10                     | G8E      | 305    |
| FA05 230-400 | 230                    | 184             | 330           | 132                                 | 67             | 97               | IK10                     | G8E      | 340    |
| FA05 270-400 | 270                    | 216             | 390           | 155                                 | 79             | 114              | IK10                     | G8E      | 385    |
| FA05 320-400 | 320                    | 256             | 460           | 185                                 | 97             | 140              | IK10                     | G8E      | 415    |
| FA05 360-400 | 360                    | 288             | 520           | 210                                 | 110            | 159              | IK10                     | G8E      | 430    |
| FA05 410-400 | 410                    | 328             | 590           | 236                                 | 123            | 178              | IK10                     | G8E      | 450    |
| FA05 450-400 | 450                    | 360             | 650           | 260                                 | 138            | 199              | IK10                     | G8E      | 475    |
| FA05 500-400 | 500                    | 400             | 720           | 288                                 | 152            | 219              | IK10                     | G8E (II) | 490    |
| FA05 550-400 | 550                    | 440             | 790           | 310                                 | 167            | 241              | IK10                     | G8E (II) | 530    |
| FA05 600-400 | 600                    | 480             | 865           | 340                                 | 182            | 263              | IK10                     | G8E (II) | 720    |

(1) Sizing realized considering the working load at full power and an average  $\cos \varphi$  of the line = 0.80