



## 5 Set-up

### 5.1 Imposicion C/K



Apretar por 5 segundos



Mediante la teclas  y  imponer el valor aconsejado en la tabla.

C/K	Power 1 <sup>st</sup> bank (K var)							
T.A. - C.T.	5	6	10	12,5	20	25	40	50
30/5	5	5	-	-	-	-	-	-
50/5	3	4	5	-	-	-	-	-
60/5	3	4	5	5	-	-	-	-
80/5	3	3	5	5	-	-	-	-
100/5	3	3	3	4	5	-	-	-
150/5	2	3	3	3	5	5	-	-
200/5	2	2	3	3	3	4	5	-
250/5	2	2	3	3	3	3	5	5
300/5	2	2	2	3	3	3	4	5
400/5	2	2	2	2	3	3	3	4
500/5	1	2	2	2	3	3	3	3
600/5	1	1	2	2	2	3	3	3
800/5	1	1	2	2	2	2	3	3
1000/5	1	1	1	2	2	2	3	3
1200/5	1	1	1	1	2	2	2	3
1500/5	1	1	1	1	2	2	2	2
2000/5	1	1	1	1	1	1	2	2
2500/5	1	1	1	1	1	1	2	2
3000/5	1	1	1	1	1	1	2	2
4000/5	1	1	1	1	1	1	1	2

Para corriente media sobre el circuito amperimetrico (secundario T.A.) inferior a 2A imponer un valor de C/K superior.

En caso de utilizacion en red trifasica a 220Vac el valor de la tabla debe ser duplicado.

El simbolo “-” en la tabla indica la instalacion de un T.A. con valor primario muy pequeño.