

CONFIGURATIONS

Notes

- In order to make capacitor banks, it is necessary to use suitable discharge resistors and current peak limiting systems upon insertion, compatibly with the characteristics of the capacitors (25 A / μ F).

Table

THD(I)_{max.} = 10% on the network

Code	Capacitance μ F	50Hz			Terminals	Execution	Dimensions D x H
		kVAr	V	A			
8302273	3 x 15,5	2,5	415	3,5	faston	resin	60 x 200
8302478	3 x 31	5	415	7	faston	resin	60 x 200
8302579	3 x 62	10	415	14	M8	resin	85 x 200
8302588	3 x 77	12,5	415	17,4	M8	resin	85 x 200
8302599	3 x 92	15	415	20,9	M8	resin	85 x 295
8302610	3 x 123	20	415	27,8	plug	resin	100 x 285
8302622	3 x 154	25	415	34,8	plug	resin	100 x 285
8304371	3 x 27,5	5	440	6,5	faston	resin	70 x 215
8304811	3 x 55	10	440	13,1	M8	resin	85 x 200
8304813	3 x 66	12,5	440	16,4	M8	resin	85 x 200
8304804	3 x 109	20	440	26,2	plug	resin	100 x 310
83048085	3 x 137	25	440	32,8	plug	resin	100 x 310
8304854	3 x 274	50	440	65,6	plug	resin	136 x 310
8306819	3 x 77	20	525	22	plug	resin	100 x 310
8306827	3 x 96	25	525	27,5	plug	resin	120 x 310
8306832	3 x 115	30	525	33	plug	resin	120 x 310
8306840	3 x 154	40	525	44	plug	resin	136 x 310

Other solutions are available upon request.